


AIR+

Carbon monoxide detector

Nexelec



Connected

Remote maintenance without entering the home



Interconnection

Up to 25 wirelessly interconnected accessories



Temperature / Humidity

Measures home environment parameters

 Carbon monoxide

 Temperature

 Humidity

Digital detector logbook


QR Code + application for monitoring installation and maintenance of a fleet of detectors

Indoor air quality

The detector continuously monitors ambient CO levels and alerts you when it's time to check that the gas boiler is operating correctly.

CO pre-alarm

Before the audible alarm is triggered, a red light flashes if abnormal abnormal CO levels are detected



3M adhesive fastener

CE and NF approved for installation without screws or plugs. No need to drill hazardous substrates (asbestos)

Electronic maintenance certificate

After each maintenance operation, a unique certificate is recorded in the detector's secure NFC chip

Compatible with the boiler cut-off ⁽¹⁾

If an alarm is triggered, the detector wirelessly interconnects with the RELAY accessory to shut down the gas boiler

Factory-calibrated CO sensor

To ensure reliable measurements throughout the detector's entire lifetime

Universal mounting base compatible ⁽¹⁾

Simplifies replacement of other brands of detectors without drilling new mounting holes



AIR+

Carbon monoxide detector

Nexelec














www.nexelec.fr








Net weight: 150 g (including battery and stand)

Reference	Battery	Radio
X850LS	10 years	LoRaWAN

FUNCTIONS

 <p>Anti-tear detection Triggers an alert message in the application if the detector is removed from its mounting base</p>	 <p>10-years battery⁽²⁾ Sealed and welded lithium battery</p>	<p>TEST</p> <p>Test/Silence button Large, easy-to-reach touch button on front panel</p>	 <p>Silence function Stops the alarm and/or puts the detector on standby for 5 minutes without removing it from its base</p>
 <p>Compact mounting base Only 3 cm in diameter to avoid damaging the installation surface</p>	 <p>Air 360° Exclusive detection technology. Simplifies detector maintenance</p>	 <p>Insect barrier Pest protection grid integrated into the detector</p>	 <p>Signal light Discreet LED indicator in standby mode, powerful in alarm mode</p>
 <p>Powerful audible alarm 85 dB at 3 metres to quickly alert occupants</p>	 <p>12-hour beep delay Temporarily silences fault beeps until detector is replaced</p>	 <p>Remote surveillance compatible⁽¹⁾ To report alarms, carry out troubleshooting or arrange on-site intervention by an approved company</p>	 <p>Calibration certificate Temperature and humidity measurement accuracy validated by an independent COFRAC-accredited laboratory</p>
 <p>Rip-off protection Lockable mounting base to reduce the risk of detector removal in rental housing</p>	 <p>Design Facilitates acceptance of the detector by residents</p>		

FEATURES

 <p>Carbon monoxide Technology: CO detection by electrochemical sensor CO: 0 - 1 000 ppm Resolution: 1 ppm</p>	 <p>Temperature Res.: 0.1°C Acc.: ±0.2°C Measurement range: -30°C to +70°C</p>	 <p>Humidity Res.: 0.5% R.H. Acc.: ±2% R.H. Measuring range: 0 - 100% R.H.</p>	 <p>Connectivity LoRaWAN</p>
<p>Terms of use Indoor environment Temperature: -10°C to +50°C Humidity: 10% RH to 95% RH (non-condensing)</p>	<p>Mounting type Wall, ceiling or free-standing</p> <p>Warranty⁽²⁾ 5 years</p>	<p>Set contents 1 detector 1 mounting base 1 removable bracket for free-standing installation 1 adhesive fastener 2 nylon screws and plugs 1 user manual</p>	<p>Certification EN50291</p> 

⁽¹⁾ Optional accessory or function available on request ⁽²⁾ The battery is designed for a non-guaranteed life of 10 years: battery life may vary. Please refer to the «Precautions and Limitations» section of the user manual.

⁽³⁾ Please refer to the «Warranty» section of the user manual.