

Nexelec



Design

Facilitates acceptance of the detector by residents

Digital logbook detector follow-up



QR Code + Application for monitoring installation and maintenance of a fleet of detectors

Electronic certificate maintenance



After each maintenance operation, a unique certificate is recorded in the detector's secure NFC chip

Universaly compatible mounting base(1)


Simplifies replacement of other brands of detectors without drilling new mounting holes

Rip-off protection

Lockable mounting base to reduce the risk of detector removal

Reduce false alarms

Electronic self-compensation for dust in the detection chamber



Compatible with 3M adhesive mounting⁽¹⁾

CE approved for installation without screws or plugs. No need to drill hazardous substrates (asbestos)

10-year battery (2)

Sealed and welded lithium battery

Test / Silence button

Large, easy-to-reach touch button on front panel

Silence function

Stops the alarm and/or puts the detector on standby for 10 minutes without removing it from its base

Compact mounting base

Only 3 cm in diameter to avoid damaging the installation surface







www.nexelec.fr

Reference Battery X820LT 10 ans



Net weight: 150 g (including battery and stand)

FUNCTIONS



8-hour beep delay

Temporarily silences fault beeps until detector is replaced



Insect barrier

Pest protection grid integrated into the detector



Signal light

Discreet LED indicator in standby mode, powerful in alarm mode



Powerful audible alarm

85 dB at 3 metres to quickly alert occupants

FEATURES

Heat

Technology: Thermistor high sensitivity (class A) with tripping threshold at 58°C

Terms of use

Warranty (3)

5 years

Indoor environment Temperature: -10°C to +50°C Humidity: 0% RH to 99% RH (noncondensing)

Mounting type

Wall or ceiling

Set contents

1 detector 1 mounting base 2 nylon screws and plugs 1 user manual

Certification

EN54-5 BS5446



⁽¹⁾ Optional accessory or function available on request (2) The battery is designed for a non-guaranteed life of 10 years: battery life may vary. Please refer to the «Precautions and Limitations» section of the user manual

⁽³⁾ Please refer to the «Warranty» section of the user manual.